

**EnOcean Easyclickpro flush-mounting receiver,for blinds/shutters,mount.plate**

**Product Data Sheet**



Current supply	230 V AC
Mounting method	Flush mounted (plaster)
Colour	White
Suitable for degree of protection (IP)	IP20
Suitable for venetian-/roller shutter switch	No
Push button mode	Yes
Switching mode	No
With radio controlled push button	No
Halogen free	Yes
Radio frequency	868Megahertz
2 channel	no
bi-directional	yes
energy metering	no
position detection	yes
potential-free contact	no

## EnOcean Easyclickpro flush-mounting receiver, for blinds/shutters, mount. plate

In addition to the bidirectional functions, the Easyclick receiver variant features position detection that can record and acknowledge the running times of shutters and blinds. Positions can then be visualised e.g. on the handheld transmitter D 450 FU-HS 128. The running times of the receivers are synchronised automatically when they reach their UP/DOWN end positions. The bidirectional Easyclick JR receiver can not only receive radio signals, but also transmits back its status every time it changes. For instance, the top/bottom end position of a shutter/blind can be depicted as a virtual image and visualised e.g. on the handheld transmitter D 450 FU-HS 128. The Easyclick receiver is designed to regulate shutters and blinds. • With mounting plate for screwing down in switch sockets with 60 mm pitch between device screws • With socket board for receiving pushbutton attachment, double D xx.425.xx JR for local control. A range of functions and parameters can be selected.

With pushbutton attachment:

left key UP, right key DOWN with slat adjust (standard function blind)  
left key UP, right key DOWN w/o slat adjust (function blind)  
jog mode (ON/OFF)

With Easyclick transmitter:

two-key operation UP/STOP/DOWN with slat adjust (standard function blind)  
two-key operation UP/STOP/DOWN w/o slat adjust (standard function shutter)  
jog mode (ON/OFF)  
one-key operation UP/STOP/DOWN  
safety lock for maintenance work  
automatic ON/OFF  
sun sensor / twilight sensor / wind sensor / rain sensor  
4 possible positions TOP/BOTTOM for lighting scenes  
lockout protection with window contact / window handle  
A function can be defined individually for each of the max 32 programmed transmitters  
Integrated repeater functions (1 level / 2 level) can be switched ON for each project, irrespectively of the set functions  
Separate preassigned functions and parameters when e.g. window contacts and window handles are being programmed

Technical data:

Own consumption: < 0.5 W (bistable relays)  
Transmit frequency: 868.3 MHz  
Voltage supply: 100–240 Vac/ 50–60 Hz  
Neutral conductor: required  
Ambient temperature: -20 °C to +40 °C  
Storage temperature: -40 °C to +85 °C  
Plugin terminals: max 1 x 1.5 mm<sup>2</sup>  
Housing height: 34 mm  
Rating: IP 20  
With mounting plate: for screwing down in switch sockets  
Approvals: CE; KEMA/KEUR  
Connecting data: I max 1.6 A

Material No.	Article No.	EAN-code
00366676	D 452 FU-EBIM JR UP O.A.	4010105366679

### PEHA Elektro GmbH & Co.KG

a Honeywell Company  
Daimlerstraße 4  
58553 HALVER  
DEUTSCHLAND

Tel.: 02353 9118 001  
Fax: 02353 9118 311  
mail: peha@honeywell.de  
www.peha.de

Änderungen vorbehalten. © Honeywell PEHA